

Manufacturer: National Instruments

Board Assembly Part Numbers (Refer to Procedure 1 for identification procedure):

Part Number and Revision	Description
147351A-01L or later	NI PCIe-7846
147351A-03L or later	NI PCIe-7856
147351A-04L or later	NI PCIe-7857
147351A-05L or later	NI PCIe-7858

Volatile Memory

Target Data	Type	Size	Battery Backup	User ¹ Accessible	System Accessible	Sanitization Procedure
Device Operation	FPGA	Xilinx XC7K160T (-01L, -03L, -04L) Xilinx XC7K325T (-05L)	No	Yes	Yes	Cycle Power
Onboard Memory	DRAM	512MB (-04L, -05L)	No	Yes	Yes	Cycle Power

Non-Volatile Memory (incl. Media Storage)

Target Data	Type	Size	Battery Backup	User Accessible	System Accessible	Sanitization Procedure
Device configuration	Flash	128Mbits	No			
<ul style="list-style-type: none"> • Device information • FPGA bitstream • Calibration metadata • Calibration data² 				No Yes Yes No	Yes Yes Yes Yes	None Procedure 2 Procedure 3 None

¹ Refer to *Terms and Definitions* section for clarification of *User* and *System Accessible*

² Calibration constants that are stored on the device include information for the device's full operating range. Any implications resulting from partial self-calibration can be eliminated by running the full self-calibration procedure.

Procedures

Procedure 1 –Board Assembly Part Number Identification:

To determine the Board Assembly Part Number and Revision, refer to the label applied to the surface of your product. The Assembly Part Number should be formatted as “P/N: 147351a-##L”, where “a” is the letter revision of the assembly and “##” are numbers that identify the model from the Board Assembly Part Numbers table.

Procedure 2 - Device Configuration Flash (FPGA bitstream):

You can use the NI-RIO Device Setup utility to erase the FPGA bitstream data. For more details, visit ni.com/info and enter the infocode `fpgaflashclr`.

Procedure 3 - Device Configuration Flash (Calibration Metadata):

The user-accessible areas of the Device Configuration Flash are exposed through a calibration Applications Programming Interface (API) in LabVIEW. For more details, visit ni.com/info and enter the infocode `rseriescalclr`.

Terms and Definitions

Cycle Power:

The process of completely removing power from the device and its components and allowing for adequate discharge. This process includes a complete shutdown of the PC and/or chassis containing the device; a reboot is not sufficient for the completion of this process.

Volatile Memory:

Requires power to maintain the stored information. When power is removed from this memory, its contents are lost. This type of memory typically contains application specific data such as capture waveforms.

Non-Volatile Memory:

Power is not required to maintain the stored information. Device retains its contents when power is removed. This type of memory typically contains information necessary to boot, configure, or calibrate the product or may include device power up states.

User Accessible:

The component is read and/or write addressable such that a user can store arbitrary information to the component from the host using a publicly distributed NI tool, such as a Driver API, the System Configuration API, or MAX.

System Accessible:

The component is read and/or write addressable from the host without the need to physically alter the product.

Clearing:

Per *NIST Special Publication 800-88 Revision 1*, “clearing” is a logical technique to sanitize data in all User Accessible storage locations for protection against simple non-invasive data recovery techniques using the same interface available to the user; typically applied through the standard read and write commands to the storage device.

Sanitization:

Per *NIST Special Publication 800-88 Revision 1*, “sanitization” is a process to render access to “Target Data” on the media infeasible for a given level of effort. In this document, clearing is the degree of sanitization described.