

**Board Assembly Part Number(s)**

Part Number	Description
198410K-723L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS XP, EXT TEMP
198410K-712L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS XP
198410J-823L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS VISTA, EXT TEMP
198410J-923L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS 7 PRO 32, EXT TEMP
198410J-912L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS 7 PRO 32
198410J-812L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS VISTA
198410J-716L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, WINDOWS XP, MADE IN USA, FOR ISRAEL ONLY
198410J-012L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, LOCALIZED OS
198410J-023L	MODULE ASSY, NI PXI-8108, CORE2DUO 2.5 GHZ CONTROLLER, LOCALIZED OS, EXT TEMP

**Manufacturer:** National Instruments

**Volatile Memory**

Type <sup>1</sup>	Size	User Accessible/ System Accessible <sup>2</sup>	Battery Backup?	Purpose	Method of Clearing <sup>3</sup>
DDR2 SDRAM	1+ GB	Yes/Yes	No	Controller RAM	Cycle Power
CMOS RAM	256 B	Yes/Yes	Yes	PCH CMOS	Remove CMOS battery

**Non-Volatile Memory**

Type	Size	User Accessible/ System Accessible	Battery Backup?	Purpose	Method of Clearing
CPLD	384 MacroCells	No/No	No	Power sequence / Watchdog/Trigger Router	None Available to User
EEPROM	2 Kbits	No/No	No	GPIB configuration	None Available to User
SPI Flash	16 Mbits	No/Yes	No	BIOS configuration	None Available to User
SPI Flash	16 Mbits	No/Yes	No	BIOS configuration	None Available to User

**Media Storage**

Type	Size	User Accessible/ System Accessible	Battery Backup?	Purpose	Method of Clearing
Hard Drive	250+ GB	Yes/Yes	No	Primary Disk Drive	Remove from controller <sup>4</sup>
Hard Drive	80 GB	Yes/Yes	No	Primary Disk Drive	Remove from controller <sup>4</sup>

## Terms and Definitions

**User Accessible** Allows the user to directly write or modify the contents of the memory during normal instrument operation.

**System Accessible** Does not allow the user to access or modify the memory during normal instrument operation. However, system accessible memory may be accessed or modified by background processes. This can be something that is not deliberate by the user and can be a background driver implementation, such as storing application information in RAM to increase speed of use.

**Cycle Power** The process of completely removing power from the device and its components. This process includes a complete shutdown of the PC and/or chassis containing the device; a reboot is not sufficient for the completion of this process.

**Volatile Memory** Requires power to maintain the stored information. When power is removed from this memory, its contents are lost.

**Non-Volatile** Retains its contents when power is removed. This type of memory typically contains calibration or chip configuration information, such as power up states.

---

<sup>1</sup> Calibration constants that are stored in device EEPROMs include information for the device's full operating range. Calibration constants do not maintain any unique data for specific configurations at which the device is used unless otherwise specified.

<sup>2</sup> Items are designated **No** for the following reason(s):

a) Hardware changes or a unique software tool from National Instruments are required to modify contents of the memory listed.

b) Hardware-modifying software tools are not distributed to customers for any personal access or customization, also known as non-normal use.

<sup>3</sup> The designation *None Available to User* indicates that the ability to clear this memory is not available to the user under normal operation. The utilities required to clear the memory are not distributed by National Instruments to customers for normal use.

<sup>4</sup> Since a hard drive cannot be cleared, to declassify a system containing a PXI embedded controller, the controller's hard drive must be removed as part of the declassification procedure. This can be done by removing the controller from the system or removing the hard drive from the controller during declassification. Alternatively, the hard drive can be permanently removed from the controller and a CompactPCI (cPCI) hard drive carrier/interface can be used to provide an easily-removable, bootable hard drive.