

IEEE 1394 (FireWire) VXIbus Interface Kit for PCI

NI VXI-1394 Kit

- VXI *plug&play*-compliant
- Complete VXI interface from any PCI computer
- VXI Slot 0 capability, including Resource Manager
- Optimized for register-based communication
- Word-serial (message-based) communication
- Direct trigger and interrupt control
- Direct access to VXI memory space
- Bidirectional VXI transfers
- High-performance DMA transfers using the MITE ASIC
- 12 MB/s sustained throughput across FireWire and VXI
- Capable of routing VXI-compliant external CLK10 source to the backplane

Operating Systems

- Windows 2000/NT/XP/Me/98

Recommended Software

- LabVIEW
- LabWindows/CVI
- Measurement Studio

Driver Software (included)

- NI-VXI/NI-VISA



Overview

The National Instruments VXI-1394 Kit links any PCI-based computer directly to the VXIbus using the IEEE 1394 or FireWire high-speed serial bus. The NI VXI-1394 Kit makes your computer perform as if it were plugged directly into the VXI backplane, giving your external computer the capability of an embedded computer. The VXI *plug&play*-compliant VXI-1394 Kit comes with the NI-VXI/NI-VISA software for Windows 2000/NT/XP/Me/98 to ease your VXI system development. NI-VXI/NI-VISA software features intuitive tools for troubleshooting and debugging VXI systems and programming libraries compatible with hundreds of industry-standard instrument drivers.

You can use the VXI-1394 Kit in any PCI-based computer running Windows 2000/NT/XP/Me/98. You gain flexibility, performance, and value by using a desktop PC for control of your VXI system. Each VXI-1394 Kit includes one PCI-1394 board that plugs into your PC; one VXI-1394 Slot 0 module that plugs directly into your VXI mainframe; a flexible IEEE 1394 cable; and NI-VXI/NI-VISA VXI bus interface software. Because the VXI-1394 Kit comes with NI-VXI/NI-VISA, all applications you write with NI-VXI and/or NI-VISA execute on the VXI-1394 without modifications.

Hardware

The VXI-1394 Kit interfaces your PCI-based desktop computer to the VXIbus using the FireWire high-speed serial bus, a serial bus technology used to connect external peripheral devices to the PC. FireWire also features “hot plug-in” capability so that you can easily add and configure FireWire devices such as the VXI-1394 interface to your PC without needing to power down your system. The VXI-1394 interface combines the FireWire technology with the MITE and MANTIS custom ASICs, which feature high-speed DMA and direct interrupt and trigger control to provide a low-cost, easy-to-use, and powerful VXI control solution.

The PCI-1394 board and the VXI-1394 Slot 0 module are connected using a thin, very flexible FireWire cable for easy installation and configuration of rack-mount systems. The FireWire cable is a 6-wire shielded cable with a maximum length of 4.5 m. You can connect up to 16 FireWire devices for a maximum length of 72 m.

IEEE 1394 (FireWire) VXIbus Interface Kit for PCI

Performance

Using FireWire technology, the VXI-1394 Kit can achieve a speed of 400 Mb/s across the FireWire link. Because FireWire was designed for streaming devices such as digital cameras, the VXI-1394 interface achieves a faster block throughput rate than GPIB-to-VXI controllers, but slower than MXI-2 or MXI-3 transfer speeds. Thus, for typical instrument control applications, the VXI-1394 interface is comparable to GPIB-to-VXI controllers – not MXI-2 or MXI-3. The VXI-1394 interface achieves a data transfer rate between the local computer memory and the VXIbus at rates up to 12 MB/s sustained throughput rate.

VXI Slot 0 Functionality

The single-slot, C-size VXI-1394 module is installed in Slot 0 in your VXI mainframe. The VXI-1394 module provides all Slot 0 capabilities including slot identification and bus management responsibilities. The VXI-1394 uses register-based Slot 0 functions, which the Resource Manager software in your PC uses to bring up the mainframe and begin normal operation.

VXI Triggers and Interrupts

With the VXI-1394 Kit, your computer can detect and service all VXIbus interrupt lines and VXI triggers in any or all VXI mainframes to which it is connected.

Shared Memory

With the VXI-1394 Kit installed, your computer can share system RAM over the VXIbus so other VXI devices can send data directly to your computer. Shared or dual-ported memory turns the system RAM in your computer into VXI memory and makes it appear as memory residing on a VXI device installed in the mainframe. The VXI-1394 Kit was optimized so you can increase system performance by transferring data directly to your PC from VXI instruments with DMA.



Figure 1. VXI-1394 Configuration

Ordering Information

NI VXI-1394 Kit for
Windows 2000/XP/Me/98.....778118-01
Windows NT.....778117-01
Includes one PCI-1394 interface board, one C-size VXI-1394 interface module,
NI-VXI/NI-VISA software, documentation, and a 4.5 m FireWire cable.

Hardware Only


NI VXI-1394 Module183815-01

BUY NOW!

For complete product specifications, pricing, and accessory information, call (800) 813-3693 (U.S. only) or go to ni.com/vxi.

NI Services and Support

NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing. Visit ni.com/services.



Training and Certification

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit ni.com/training.

Professional Services

Our Professional Services Team is comprised of NI applications engineers, NI Consulting Services, and a worldwide NI Alliance Partner Program of more than 600 independent consultants and integrators. Services range from start-up assistance to turnkey system integration. Visit ni.com/alliance.



OEM Support

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit ni.com/oem.

Local Sales and Technical Support

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at ni.com/support.

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit ni.com/ssp.

Hardware Services

NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with ni.com/pxiadvisor.

Calibration Services

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit ni.com/calibration.

Repair and Extended Warranty

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit ni.com/services.



ni.com • (800) 433-3488

National Instruments • Tel: (512) 683-0100 • info@ni.com

© 2005 National Instruments Corporation. All rights reserved. CVI, LabVIEW, Measurement Studios, National Instruments Alliance Partner, NI, ni.com, NI-VISA, NI-VXI, and SCXI are trademarks of National Instruments. Other product and company names listed are trademarks or trade names of their respective companies. A National Instruments Alliance Partner is a business entity independent from NI and has no agency, partnership, or joint-venture relationship with NI.