

B Series Multifunction DAQ, 16-Bit, 200 kS/s, 16 Analog Inputs

NI B Series

- Basic functionality with NI quality
- Ideal for beginning users and OEMs
- 16 analog inputs at up to 200 kS/s
- 16-bit input resolution
- 8 or 10 digital I/O lines
- Digital triggering
- Up to 4 analog input signal ranges
- NI measurement services software simplifies configuration and measurements

Operating Systems

- Windows 2000/XP
- Mac OS X
- Linux

Recommended Software

- LabVIEW
- LabWindows/CVI
- Measurement Studio
- VI Logger
- SignalExpress

Measurement Services Software (included)¹

- NI-DAQmx driver software
- Measurement & Automation Explorer configuration utility
- VI Logger Lite data-logging software

¹Mac OS X and Linux users must download NI-DAQmx Base driver.

NI recommends the M Series low-cost family.



Product	Bus	Analog Inputs ¹	Input Resolution (bits)	Aggregate Sampling Rate (kS/s) ²	Input Range (V)	Integrated Signal Conditioning	Analog Outputs	Output Resolution (bits)	Output Rate (S/s)	Output Range (V)	Digital I/O	Counter/ Timers	Triggers
PCI-6014	PCI	16 SE/B DI	16	200	±0.05 to ±10	—	2	16	10 k	±10	8	2	Digital
PCI-6013	PCI	16 SE/B DI	16	200	±0.05 to ±10	—	0	—	—	—	8	2	Digital
PCI-6010	PCI	16 SE/B DI	16	200	±0.2 to ±5	—	2	16	static	±5	10	2	Digital

¹SE—Single-ended, DI—differential ²All channels share one analog-to-digital converter.

Table 1. B Series DAQ Selection Guide

Product Description

National Instruments B Series data acquisition boards deliver economical, reliable PCI data acquisition capabilities. Consider the M Series low-cost family of data acquisition products for PCI or PXI-based data acquisition applications requiring up to 32 analog input channels, up to 48 digital I/O lines, and up to 250 kS/s sampling rates, all for about the same price as a B Series data acquisition board.

Recommended Accessories

NI offers economical connectivity options as well as higher-performance, noise-reducing options.

Model	Signal Connectivity					
	Cable		Sensors/Signals >10 V		Signals <10 V	
	Low-Cost Ribbon	Noise-Reducing	Low-Cost Portable	High-Performance	Low-Cost Unshielded	Noise-Reducing
NI 6013	R68-68	SH68-68-EP	SCC	SCC	CB-68LP	SCB-68
NI 6014						

Table 2. B Series Accessory Selection Guide

Model	Cable	Connector Block
NI 6010	SH37F-37M-1	CB-37FLP

Table 3. NI 6010 Accessory Selection Guide

Key Features

- 16-bit analog input resolution
- Low-cost data acquisition with basic functionality
- Ideal for beginning users and OEMs
- NI measurement services software

Visit ni.com/oem for information on NI custom designs and quantity discounts for OEM customers.

Ordering Information

NI PCI-6014	778627-01
NI PCI-6013	778629-01
NI PCI-6010	
NI PCI-6010	779348-01
NI PCI-6010, 50-Board Package	779348-50

Includes data acquisition driver software.


For more information on extended warranty and value-added services, visit ni.com/services.

BUY NOW!

For complete product specifications, pricing, and accessory information, call (800) 813 3693 (U.S. only) or go to ni.com/daq.

NI Services and Support

NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing. Visit ni.com/services.



Training and Certification

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit ni.com/training.

Professional Services

Our Professional Services Team is comprised of NI applications engineers, NI Consulting Services, and a worldwide NI Alliance Partner Program of more than 600 independent consultants and integrators. Services range from start-up assistance to turnkey system integration. Visit ni.com/alliance.



OEM Support

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit ni.com/oem.

Local Sales and Technical Support

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at ni.com/support.

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit ni.com/ssp.

Hardware Services

NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with ni.com/pxiadvisor.

Calibration Services

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit ni.com/calibration.

Repair and Extended Warranty

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit ni.com/services.



ni.com • (800) 813 3693

National Instruments • info@ni.com